

M6 Research, Inc. Mictor Stake Adapter Pinout MB002

Mictor – Corresponds to HP E5346 recommended pinout.

1	Testpoint	2	Testpoint
3	Testpoint	4	Testpoint
5	CLKE	6	CLKO
7	DE15	8	DO14
9	DE14	10	DO14
11	DE13	12	DO13
13	DE12	14	DO12
15	DE11	16	DO11
17	DE10	18	DO10
19	DE9	20	DO9
21	DE8	22	DO8
23	DE7	24	DO7
25	DE6	26	DO6
27	DE5	28	DO5
29	DE4	30	DO4
31	DE3	32	DO3
33	DE2	34	DO2
35	DE1	36	DO1
37	DE0	38	DO0

2X9 Header (Odd)

1	CLKO	2	GND
3	DO15	4	DO14
5	DO13	6	DO12
7	DO11	8	DO10
9	DO9	10	DO8
11	DO7	12	DO6
13	DO5	14	DO4
15	DO3	16	DO2
17	DO1	18	DO0

2X9 Header (Even)

1	DE0	2	DE1
3	DE2	4	DE3
5	DE4	6	DE5
7	DE6	8	DE7
9	DE8	10	DE9
11	DE10	12	DE11
13	DE12	14	DE13
15	DE14	16	DE15
17	GND	18	CLKE